

# 785 Terminal



SOFTWARE      HARDWARE      ACCESSORIES



Pair the 785 terminal with your time and attendance software to provide employees with a secure method for clocking in/out for shifts/breaks. Device can perform job transfers, tip collection info, etc.



The 785 is a reliable fingerprint authentication terminal for time, attendance and access control, which can connect to two additional devices for use with printers or external card readers.



785 supports power over Ethernet (POE) and includes a 2-hour operational backup battery. In the event of a power outage, employees will still be able to transfer departments and punch in and out.

## Specifications

### DATA CAPTURE FOR WORKPLACE ATTENDANCE

<b>Alphanumeric Key</b>	10
<b>Backup Battery</b>	2 hours
<b>Communication Option</b>	Ethernet (TCP/IP), Serial, Wireless (optional)
<b>Display</b>	32-character LCD back-lit screen
<b>Environment</b>	-20 to 60 Celsius, up to 95% humidity
<b>External Reader</b>	Wiegand input (2 ports)
<b>In/Out Keys</b>	Yes
<b>Input</b>	2 ports
<b>Memory Space</b>	512 Kbyte

<b>Output</b>	2 relays: sensor, access control
<b>Physical Dimensions</b>	9.8"x 6.7" x 3.7"
<b>Power</b>	12V, POE (optional)
<b>Printer Capability</b>	2 ports
<b>Programmable Function Keys</b>	4
<b>Programming</b>	ASCII-based, over communication port
<b>Registered FP Capability</b>	9,090
<b>Supported Readers</b>	Magnetic Track 1 & 11, Barcode 0 of 9 & 2 of 5, Synel Proximity, HID, Fingerprint